

Pioneer Dj



DJM-350-W 2-CHANNEL DJ MIXER WITH USB RECORDING

Pearl white gloss finish / USB Port for instant recording / 4 Innovative Effects: Filter, Short Echo, Jet, Noise / 3-band Equalising Isolator on each channel / High quality sound from isolated components / Mic / Aux Terminals / Cross Fader Curve Adjust / Track Mark button splits recording for indexed mixes / P-LOCK Fader Caps, the industry's first fader knob lock mechanism



The new DJM-350-W fuses innovative effects, high quality components and USB recording in a robust, DJ friendly design.

DJM-350-W Specifications

No. of Channels:	2 channels + 1 MIC / AUX channel
Input Terminals:	CD × 2 (RCA) PHONO × 2 (RCA) MIC × 1 (1/4 inch Jack × 1) AUX × 1 (RCA)
Output Terminals:	MASTER OUT × 2 (RCA) HEADPHONE MONITOR OUT × 1 (1/4 inch Jack) REC OUT × 1 (RCA)
Other Terminals:	Control Out × 2 (3.5mm mini-jack), USB A Port × 1
Sampling Rate:	48kHz
A/D, D/A Converter:	24-bit
Frequency Performance:	20 Hz–20 kHz
Total Harmonic Distortion:	0.007% or less
Signal/Noise Ratio:	97 dB (CD) or higher
Power Supply:	AC 220 ~ 240V (50 Hz/60 Hz)
Power Consumption:	17 W
Max External Dimensions:	218 × 301.1 × 106.6 mm (W×D×H)
Weight:	3.2 kg



Pioneer Europe N.V. Multimedia Division, Slough SL2 4QP, UK TEL +44 (0) 1753 789789

Features and specifications of the products described or illustrated in this catalogue are correct at the time of printing but could change as production changes might occur. This catalogue may contain typographical errors and the colours of the depicted products may deviate slightly from reality. Consult your Pioneer dealer to ensure that actual features and specifications match your requirements. This catalogue may contain references to products that may or will not be available in your country.

Designed and produced by Planet Interactive Arts Limited, www.planet-ia.com DJM-350-W-2PP-PEE

videos on
DJSOUNDS.COM