

Pioneer Dj

DDJ-RX

**NEXT
GENERATION**

- PLUG-AND-PLAY WITH REKORDBOX DJ PLUSPACK (INCLUDED)
- MULTI-COLOURED PERFORMANCE PADS
- 4-CHANNEL MIXER
- PAD FX
- SEQUENCER
- SOUND COLOR FX
- BEAT FX
- RELEASE FX
- SLIP MODE
- QUANTIZED BEAT JUMP
- HOT CUES
- SLICER



rekordbox dj

EXPLORE THE REKORDBOX DJ
PLUS PACK AT [REKORDBOX.COM](https://www.rekordbox.com)
SAME FAMILIAR REKORDBOX,
NEW PERFORMANCE CAPABILITIES

DDJ-RX


NATIVE CONTROL OF REKORDBOX DJ

MAIN SPECIFICATIONS

Software	rekordbox dj
Input ports	CD x 2 (RCA) Line/Phone x 2 (RCA) MIC x 2 (XLR & ¼-inch TRS jack x 1, ¼-inch TRS jack x 1)
Output ports	Master Out x 2 (RCA x 1, XLR x 1), Booth Out x 1 (¼-inch TRS jack) Headphone Monitor Out x 2 (Front ¼-inch TRS jack, 3.5 mm stereo mini jack)
Other ports	USB (Type B) x 1
Frequency response	20 Hz ~ 20 kHz
Total Harmonic Distortion ratio	0.003% or less (PC)
S/N ratio	107 dB or above (PC)
Maximum dimensions (W X D X H)	664 x 353.4 x 70.4 mm
Unit weight	5.8 kg

REKORDBOX DJ SYSTEM REQUIREMENTS

Compatible OS (Windows)	Windows 10 / Windows 8.1 Pro / Windows 8.1 / Windows 8 Pro / Windows 8 (The latest service pack) Windows® 7 Home Premium / Professional / Ultimate (The latest service pack) Intel® Processor Core i3 / i5 / i7
Compatible OS (Mac)	Mac OS X 10.10, 10.9, 10.8 (Updated to the latest version) Intel® Processor Core i3 / i5 / i7 4 GB or more of RAM
Hard Drive	250 MB or more of free space (not including space for storing music files, etc.)
Sound	Audio output to speakers, headphones, etc. (internal or external audio device)
USB port	A USB 2.0 port is used to connect a controller or a mixer, and export track files to a USB storage device such as a flash drive and a hard disk drive
Playable music file	MP3, AAC, WAV, AIFF, ALAC, FLAC
Internet connection	Internet access is needed to create a rekordbox account and to download and activate the software
Display resolution	Resolution of 1280 x 768 or greater



MIRRORS THE REKORDBOX DJ GUI

Tight integration for intuitive creative performances.



PAD FX

Create multiple FX chains using all 16 pads.



SEQUENCER

Record and loop sample sequences on the fly.

