

CD Receiver with Bluetooth(R) Wireless Technology and Front USB/AUX Input



MOS-FET 50W x 4

Sub Woofer Direct Connection (Mono Lch)

Bluetooth(R) Wireless Technology*1 (Built-in)

(Hands-Free Call (HFP 1.6 wideband speech), 2 Phones Full-Time

Connection, Audio Streaming & Control (A2DP, AVRCP), Voice

Recognition Dialing, Siri Eyes Free, Phone Book Access Profile

(PBAP), iPhone & Android Automatic Pairing)

JVC Smart Music Control (via Bluetooth(R))

iPod/iPhone Music Playback

Android AUDIO MODE and AUTO MODE *2

Media Playback: WAV / MP3 / WMA / FLAC

AUX Input (Front)

Digital Processing Tuner

K2 Technology

Space Enhancement

Sound Response

Sound Lift

Volume Link EQ

13-Band Graphic EQ

8-Preset EQ

4.0V Line and Subwoofer Pre-Output Level

3 Pairs (Front + Rear + Subwoofer)

3-Zone Variable Colour Illumination

Steering Wheel Remote Ready

*1 Available functions depend on cell phone.

*2 Android (Ver 4.1 and above) AUTO MODE requires JVC Music Play Application.

2-DIN CD Receiver

CD Receivers/Digital Media Receivers	KW-R920BTE
Media Playback	
MP3/WMA Compatible with ID3 Tag/WMA Tag	CD / USB
WAV Compatible with Tag	USB
FLAC Compatible with Tag	USB
CD Player	
CD-R/RW Compatible	•
CD Text	•
Random/Repeat Play	•
Frequency Response	20 - 20,000Hz (+/-1dB)
Dynamic Range	90dB
Signal-to-Noise Ratio	105dB (1kHz)
Channel Separation	85dB
Wow & Flutter	Below measureable limit
Bluetooth Control	
Bluetooth Control [5]	• (Built-in, Wired-Mic included)
2 Phones Full-Time Connection	•
Hands Free Call (HFP)	• (HFP 1.6 wideband speech)
Audio Streaming & Control (A2DP, AVRCP)	•
Voice Recognition Dialing (compatible mobile phone required)	•
Siri E• Free Mode for iPod/iPhone	•
Phone Book Access Profile (PBAP)	•
iPhone & Android Automatic Pairing	•
Android Control	
Android Music Playback (AUDIO MODE and AUTO MODE)	• (AUDIO MODE & AUTO MODE)[6]
JVC Smart Music Control	• (via Bluetooth(R))
Battery Charge	• (USB: 1.5A Max.)
iPod/iPhone Control	
iPod/iPhone Music Playback	•
Random/Repeat Play	•
Text	•
Battery Charge	• (USB: 1.5A Max.)
USB	
Position	Front
Random/Repeat Play	•
USB Power Supply	• (1.5A)
USB Mass Storage Class (for music files)	•
Drive Change Mode for Mass Storage Class	•
Tuner	
Radio Data System (RDS)	• (with Radio Text Plus)
Digital Processing Tuner	•
Preset Stations	18FM + 6AM
Strong Station Memory (for FM)	•
Radio Timer	• (Once/Daily/Weekly)
Tuner Preset Memory (for power disconnection)	•
FM	
Frequency Range	87.5 - 108.0MHz
Usable Sensitivity	8.2dBf (0.71uV/75 ohms)
Quieting Sensitivity (46dB)	17.2dBf (2.0uV/75 ohms)
Stereo Separation	40dB
AM	
Frequency Range	(MW) 531 - 1,611kHz (9kHz), (LW) 153 - 279kHz (9kHz)
Sensitivity	(MW) 28.2uV, (LW) 50uV
Audio	
Maximum Power Output	50W x 4 / 50W x 2 +Subwoofer (4 ohms) 50W x 1
Typical Power Output	22W x 4 (Full Bandwidth Power, at less than 1% THD)
MOS-FET Amplifier	•
Sub woofer Direct Connection (Mono Lch)	•
Audio DAC	•
EQ	
13-Band Graphic EQ	•
Easy EQ Setting	•
Preset EQ	• (8-preset)
Source Link EQ	•
Loudness Control	• (Off/Low/High)
High-Pass Filter/Low-Pass Filter	•/•
K2 Technology	•
Space Enhancement	•
Sound Response	•
Sound Lift	•
Volume Link EQ	•
Load Impedance	4 ohms (4 - 8 ohms)
Pre-Output Level	4.0V
Line Output Impedance	Less than 600 ohms
Subwoofer Output Level	4.0V

Inputs and Outputs	
AUX Input	1 (Front)
Line Output Terminals (Pair)	3 Pairs (Front + Rear + Subwoofer)
Subwoofer Output with Level/Frequency Control	• (Level -50 - +10)
Display	
Display Type	
Variable Colour	• (3-Zone)
Illumination Colour	Variable (3-Zone)
Russian Text Display Compatible	•
Spanish Text Display Compatible	•
Auto Dimmer	•
Brightness Control	•
General	
Steering Remote Control Ready	•
ISO Connector	Cable
Dimensions (W x H x D)	
Installation Size	178 x 112 x 158mm
Weight	1.6kg

[5] Available functions depend on mobile phone. [6] Android (Ver 4.1 and above) AUTO MODE requires JVC Music Play Application.